



(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
 02.02.2000 Bulletin 2000/05

(51) Int. Cl.⁷: **G01R 31/36**

(21) Application number: 99114682.0

(22) Date of filing: 27.07.1999

(84) Designated Contracting States:
**AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
 MC NL PT SE**
 Designated Extension States:
AL LT LV MK RO SI

(30) Priority: 28.07.1998 JP 21267198
 31.07.1998 JP 21744198

(71) Applicant:
NTT Power and Building Facilities Inc.
Tokyo (JP)

(72) Inventors:
 • Murao, Tetsuro,
 c/o NTT Power and Building F. Inc.
Tokyo (JP)

• Motozu, Tamotsu,
 c/o NTT Power and Building F. Inc
Tokyo (JP)
 • Tsujikawa, Tomonobu,
 c/o NTT Power and Building
Tokyo (JP)
 • Kawagoe, Yuji,
 c/o NTT Power and Building F. Inc.
Tokyo (JP)

(74) Representative:
Schmidt-Evers, Jürgen, Dipl.-Ing. et al
Patentanwälte Mitscherlich & Partner,
Sonnenstrasse 33
80331 München (DE)

(54) **Apparatus for managing a battery unit having storage batteries**

(57) The voltages V of storage batteries (S_a , S_b , ... S_n) are detected, and the voltage E of the battery unit (10) is detected. A defect in each storage battery is detected in accordance with the voltage V detected. An abnormal voltage of the battery unit (10) is detected in accordance with the voltage E detected. Further, the

temperature T of the battery unit (10) is detected, on the basis of which the expiration of each storage battery is determined. The defect detected; the abnormal voltage detected, and the expiration determined are informed.




FIG. 1

BEST AVAILABLE COPY

EP 0 977 047 A2

Description

[0001] The present invention relates to an apparatus for managing a battery unit to be incorporated into, for example, an uninterruptible power supply system.

[0002] The uninterruptible power supply system comprises a battery unit. Power is supplied from the battery unit to a load when the commercial AC power supply fails to supply power, whereby the load can be driven without break. The battery unit comprises a plurality of storage batteries connected in parallel or in series.

[0003] In the uninterrupted power supply system it is necessary to inspect each storage battery periodically.

[0004] Recently, sealed-type lead storage batteries are used in great quantities as storage batteries. The jar of a sealed-type lead storage battery is sealed. This makes it impossible to determine whether the electrodes in the jar have been corroded or whether the electrolyte in the jar is insufficient in amount. It is therefore very difficult to detect whether each storage battery is defective (due to, for example, manufacturing errors) or has expired.

[0005] If any one of the storage batteries is defective or has expired, the battery unit may no longer supply power to the load.

[0006] The present invention has been made in view of the foregoing. Its object is to provide an apparatus for automatically managing, with high reliability, a battery unit having storage batteries, which can reliably detect and inform a defect in each storage battery and an abnormal voltage in the battery unit and reliably determine and inform the life of each storage battery, without requiring the service of inspection-maintenance workers.

[0007] An apparatus according to the present invention is designed to manage a battery unit having a plurality of storage batteries and comprises:

a plurality of first voltage detecting means for detecting voltages of the storage batteries, respectively;

second voltage detecting means for detecting a total voltage of the battery unit;

defect detecting means for detecting defects in the storage batteries on the basis of the voltages detected by the first voltage detecting means;

abnormality detecting means for detecting an abnormal voltage in the battery unit on the basis of the voltage detected by the second voltage detecting means;

temperature detecting means for detecting temperature in the battery unit;

battery life determining means for determining a life of each of the storage batteries has dead, on the basis of the temperature detected by the temperature detecting means; and

information means for informing results of the detection performed by the defect detecting means

and abnormality detecting means and results of the determination made by the battery life determining means.

[0008] This summary of the invention does not necessarily describe all necessary features so that the invention may also be a sub-combination of these described features.

[0009] The invention can be more fully understood from the following detailed description when taken in conjunction with the accompanying drawings, in which:

FIG. 1 is a block diagram showing an embodiment of this invention and an uninterruptible power supply system incorporating the embodiment;

FIG. 2 is a flow chart for explaining the operation of this embodiment;

FIG. 3 is a flow chart continuous to the flow chart shown in FIG. 2;

FIG. 4 is a chart for explaining how to determine the operation mode of the embodiment;

FIG. 5 is a chart for explaining how defects are detected in the embodiment operating in the float charge mode;

FIG. 6 is a chart for explaining how defects are detected in the embodiment operating in the discharge mode;

FIG. 7 is a chart for explaining how defects are detected in the embodiment operating in the float charge mode;

FIG. 8 is a chart for explaining how an abnormal voltage is detected in the battery unit in the embodiment;

FIG. 9 is a diagram showing a storage battery related to the embodiment and a connecting device used in the embodiment;

FIG. 10 is a view showing a washer used in the embodiment; and

FIG. 11 is a sectional view of the female tab used in the embodiment.

[0010] An embodiment of the present invention will be described, with reference to the accompanying drawings.

[0011] As shown in FIG. 1, a rectifier 2 is connected to a commercial AC power supply 1. An inverter 3 is connected to the output terminals P and N of the rectifier 2 by DC power supply lines L1 and L2.

The inverter 3 is switched, converting the output voltage of the rectifier 2 (a DC voltage) to an AC voltage having a predetermined frequency. The output of the inverter 3 is supplied to a load 4.

[0012] A battery unit 10 is connected between the DC power supply lines L1 and L2. The battery unit 10 comprises a plurality of storage batteries Sa, Sb, ... Sn, which are connected in series. Each storage battery is a sealed-type lead storage battery.

[0013] The battery unit 10 can be operated in various

modes, which are float charge mode, discharge mode and recharge mode.

[0014] In the float charge mode, the voltage of the power supply (rectifier 2) is applied to the load (inverter 3) connected to the battery unit 10, and the battery unit 10 is recharged by virtue of the voltage of the power supply (rectifier 2).

[0015] In the discharge mode, the voltage of the battery unit 10 is applied to the load (inverter 3) when the voltage of the power supply (rectifier 2) falls or is zero (when the supply of power is interrupted).

[0016] In the recharge mode, the battery unit 10 is recharged by virtue of the voltage of the power supply (rectifier 2), after the battery unit has operated in the discharge mode.

[0017] The rectifier 2, inverter 3 and battery unit 10 constitute an uninterruptible power supply system that keeps driving a load even if the commercially AC power supply 1 is interrupted.

[0018] In this uninterruptible power supply system, voltage detecting sections (first voltage detecting means) 11a, 11b, ... 11n are connected to the storage batteries Sa, Sb, ... Sn of the battery unit 10, respectively, to detecting the voltages V of the storage batteries Sa, Sb, ... Sn. Further, a temperature detecting section 12 is provided for the battery unit 10. The temperature detecting section 12 has a temperature sensor 12a attached to the battery unit 10. The temperature sensor 12a detects the temperature T of the battery unit 10 (or the ambient temperature of the battery unit 10).

[0019] A total voltage detecting section (second voltage detecting means) 13 is connected between the DC power supply lines L1 and L2, to detect the total voltage E of the battery unit 10.

[0020] A measuring section 21, a parameter setting section 22, a display section 23, and an alarm generating section 24 are connected to a control section 20.

[0021] The measuring section 21 performs A/D (analog-to-digital) conversion on the voltages V detected by the voltage detecting sections 11a, 11b, ... 11n, the temperature T detected by the temperature detecting section 12, and the voltage E detected by the total voltage detecting section 13, thereby generating digital data. The digital data is supplied to the control section 20.

[0022] The parameter setting section 22 is designed to set various parameters for operating the control section 20.

[0023] The display section 23 displays (informing) the results of operation of the control section 20.

[0024] The alarm generating section 24 generates an alarm signal when the control section 20 detects a defect in any one of the storage batteries, detects an abnormal voltage in the battery unit 10, or determines that the death of any one of the storage batteries (namely, the death of the battery unit 10). The alarm signal is transmitted (or given) to a central control room where inspection-maintenance workers are stationed.

[0025] The control section 20 has the following func-

tional means [1] to [8]:

[1] Operation mode determining means for determining in which mode the battery unit 10 is operating, float charge mode, discharge mode, or recharge mode.

[2] First defect detecting means for detecting defects in the storage batteries Sa, Sb, ... Sn in accordance with whether the voltages V detected by the voltage detecting sections 11a, 11b, ... 11n are lower than a predetermined low voltage V_2 , if the operation mode determining means determines that the battery unit 10 is operating in the float charge mode.

[3] Second defect detecting means for detecting defects in the storage batteries Sa, Sb, ... Sn in accordance with whether the voltages V detected by the voltage detecting sections 11a, 11b, ... 11n are equal to or higher than a predetermined high voltage V_3 , if the operation mode determining means determines that the battery unit 10 is operating in the float charge mode.

[4] Third defect detecting means for detecting defects in the storage batteries Sa, Sb, ... Sn in accordance with whether the voltages V detected by the voltage detecting sections 11a, 11b, ... 11n are lower than a predetermined low voltage V_1 ($< V_2$) upon lapse of a prescribed time (e.g., one minute) from the start of the discharge mode, if the operation mode determining means determines that the battery unit 10 is operating in the discharge mode.

[5] First abnormality detecting means for detecting an abnormal voltage in the battery unit 10 in accordance with whether the voltage E detected by the total voltage detecting section 13 remains equal to or higher than a predetermined maximum value E_{max} for a prescribed time (alarm masking time) ta.

[6] Second abnormality detecting means for detecting an abnormal voltage in the battery unit 10 in accordance with whether the voltage E detected by the total voltage detecting section 13 remains lower than a predetermined minimum value E_{min} for a prescribed time (alarm masking time) tb.

[7] Life determining means for calculating an average of temperatures T detected by the temperature detecting section 12 at regular intervals (e.g., every hour), and for determining the life of the storage batteries Sa, Sb, ... Sn (namely, the life of the battery unit 10) on the basis of the relation between the average temperature and Arrhenius' rule.

[8] Information means for informing the defects detected by the various defect detecting means, the abnormalities detected by the various abnormality detecting means, and the life determined by the life detecting means.

[0026] The operation of the structure described above

will be described, with reference to the flow chart of FIGS. 2 and 3.

[0027] At first, time counts t_1 , t_2 , t_3 and t_4 are cleared (Step 101).

[0028] Upon lapse of a predetermined time, e.g., one hour, the temperature of the battery unit 10 is detected (if YES in Step 100). At the timing of detecting the temperature, the average (temperature of the battery unit 10) of the temperatures T that the temperature detecting section 12 has detected is calculated. On the basis of the relation between the average temperature and Arrhenius' rule, the life of the storage batteries S_a , S_b , ... S_n (namely, the life of the battery unit 10) are determined (Step 102). If any storage battery is found to have dead (if YES in Step 103), the display section 23 displays this event and the alarm generating section 24 generates an alarm signal (Step 104).

[0029] The voltage E detected by the total voltage detecting section 13 may become equal to or higher than the predetermined maximum value E_{max} (if YES in Step 105), as in Case A illustrated in FIG. 8. In this case, the time count t_1 is started (Step 106). When the time count t_1 reaches the prescribed value t_a (if YES in Step 107), it is determined that the total voltage E is abnormal (Step 108). The display section 23 displays this event and the alarm generating section 24 generates an alarm signal (Step 109).

[0030] The voltage E detected by the total voltage detecting section 13 may fall below predetermined minimum value E_{min} (if YES in Step 110), as in Case B illustrated in FIG. 8. If this happens, the time count t_2 is started (Step 111). When the time count t_2 reaches the prescribed value t_b (if YES in Step 112), it is determined that the total voltage E is abnormal (Step 108). The display section 23 displays this event and the alarm generating section 24 generates an alarm signal (Step 109).

[0031] The voltage E detected by the total voltage detecting section 13 (i.e., the total voltage) is compared with values E_1 and E_2 ($E_1 < E_2$), the value E_1 preset for detecting discharge and the value E_2 preset for detecting the end of discharge (Step 113).

[0032] If the voltage E detected is equal to or higher than the preset value E_2 (if YES in Step 113), it is determined that the battery unit 10 is operating in the float charge mode (Step 114). In this case, the low voltage V_2 and the high voltage V_3 are selected, both preset as reference values for detecting defects in the storage batteries (Step 115).

[0033] The voltage V detected by any one of the voltage detecting sections 11a, 11b, ... 11n may fall below the low voltage V_2 as shown in FIG. 5, while the battery unit 10 is operating in the float charge mode. If so (if YES in Step 116), it is determined that the storage battery causing this voltage drop is defective (Step 118). The display section 23 displays this event and the alarm generating section 24 generates an alarm signal (Step 119).

[0034] The voltage V detected by any one of the volt-

age detecting sections 11a, 11b, ... 11n may rise to or above the high voltage V_3 as shown in FIG. 7, while the battery unit 10 is operating in the float charge mode. If this happens (if NO in Step 116 and YES in Step 117), it is determined that the storage battery causing this voltage rise is defective (Step 118). The display section 23 displays this event and the alarm generating section 24 generates an alarm signal (Step 119).

[0035] The voltage E detected may fall below the preset value E_2 (NO in Step 113) and may be lower than the preset value E_1 (Step 120). If so, it is determined that the battery unit 10 is operating in the discharge mode (Step 121). In this case, the low voltage value V_1 ($< V_2$) is selected as reference for detecting a defect in each of the storage batteries (Step 122).

[0036] In the discharge mode, the time count t_3 is started at the same time it is determined that the battery unit 10 is operating in the discharge mode (Step 123). When the time count t_3 reaches one minute (i.e., the detecting masking time) (YES in Step 124), the voltages V detected by the voltage detecting sections 11a, 11b, ... 11n are compared with the low voltage value V_1 ($< V_2$) selected (Step 125).

[0037] If any one of the voltages V detected is lower than the preset low voltage value V_1 as shown in FIG. 6 (if YES in Step 125), it is determined that the storage battery causing this voltage drop is defective (Step 118). The display section 23 displays this event and the alarm generating section 24 generates an alarm signal (Step 119).

[0038] If the detected voltage E rises to or above the preset value E_1 (if NO in Step 120) and if the discharge mode is no longer valid (if YES in Step 126), it is determined that the battery unit 10 is operating in the recharge mode (Step 127). At the same time it is determined so, the time count t_4 is started (Step 128). Until the time count t_4 reaches 48 hours (if NO in Step 129), it is determined that recharge mode remains valid, regardless of changes in the detected voltage E (Step 127). Thus, for 48 hours corresponding to the time count t_4 , it is not determined whether or not a defect exists in each storage battery (detection masking).

[0039] As informed above, an abnormal voltage of the battery unit 10 and defects in the storage batteries S_a , S_b , ... S_n can be reliably detected without requiring the service of inspection-maintenance workers. In addition, the life of each storage battery can be determined and informed without requiring the service of inspection-maintenance workers.

[0040] The battery unit 10 and the storage batteries S_a , S_b , ... S_n can be automatically managed with high reliability.

[0041] The voltage detecting sections 11a, 11b, ... 11n are connected to the battery unit 10 and storage batteries S_a , S_b , ... S_n by means of the connecting device shown in FIGS. 9, 10 and 11. These figures illustrate only the connection of the storage battery S_a and the voltage detecting section 11a. Any other voltage detect-

ing section is connected to the associated storage battery in the same manner.

[0042] The storage battery Sa has a pair of bolt-shaped electrodes 41, which protrude from the upper surface of the sealed jar 40.

[0043] An electrically conductive washer 30 is secured to each of the electrodes 41. A connecting member 50, known as "female tab," is attached to the washer 30. A wire 58 is led from the female tab 50 and is connected to the voltage detecting section 11a.

[0044] A nut 42 is mounted on each electrode 41 of the storage battery Sa. The washer 30 and a connecting member 60 are attached to each electrode 41 in the order mentioned, and the nut 42 is fastened, gripping the electrode 41. The wire 61 led from each connecting member 60 is connected to one electrode 41 of the next storage battery Sb.

[0045] As shown in FIG. 10, the washer 30 has a ring-shaped part 32 and a flat connecting strip 33. The strip 33 outwardly protrudes from the ring-shaped part 32 in the radial direction and can be attached to and removed from the electrode 41. The electrode 41 can pass through the hole 31 of the ring-shaped part 32. The connecting strip 33 has such shape and size that it can be sufficiently inserted in the female tab 50 even when the nut 42 is fastened, gripping the electrode 41.

[0046] The female tab 50 comprises a housing 51 made of insulating material, a recess 52 made in one end of the housing 51, a pair of electrically conductive holding members 53 provided in the recess 52, a conductor 54 provided in the recess 52 and electrically connected to the holding members 53, a part-accommodating hole 55 extending from the bottom of the recess 52 to the proximal end 58a of a wire 58, and a series circuit composed of a fuse 56 and a resistor 57 which are provided in the part-accommodating hole 55.

[0047] One end 56a of the fuse 56 is connected to the conductor 54. The other end of the fuse 56 is connected by the resistor 57 to the proximal end 58a of the wire 58.

[0048] The resistor 57 functions as a protection resistor for preventing short-circuiting, if any in the load (i.e., wire 58 or voltage detecting section 11a), from changing the voltage of the storage battery Sa. The fuse 56 melts to prevent an excessively large current from flowing through the female tab 50 if short-circuiting or the like occurs in the load (i.e., wire 58 or voltage detecting section 11a).

[0049] The recess 52 is formed so large that the connecting strip 33 can be fully inserted into it. Each holding member 53 has been formed by bending a thin metal plate having electrical conductivity.

The holding members 53 work like leaf springs, reliably contacting and clamping the connecting strip 33 inserted in the recess 52. Due to the clamping, the washer 30 and the wire 58 are electrically connected to each other by the holding members 53, conductor 54, fuse 56 and resistor 57. Each holding member 53 is inclined or curved in the open end of the recess 52, so

that the connecting strip 33 may be smoothly inserted into the recess 52.

[0050] As described above, a washer 30 is fastened on each electrode 41 of the storage battery Sa, and a female tab 50 is attached to the connecting strip 33 of the washer 30. The storage battery Sa and the voltage detecting section 11a can thereby connected easily and reliably. That is, the voltage detecting section 11a can be easily connected to the storage battery Sa, without removing the nut 42 or the connecting member 60 from the electrode 41 and without suspending the operation of the uninterruptible power supply system. Further, the efficiency of connecting the section 11a to the battery Sa is enhanced.

[0051] Since each holding members 53 of the female tab 50 reliably contacts the connecting strip 33 of the washer 30, stable and good electrical connection is maintained between the storage battery Sa and the voltage detecting section 11a.

[0052] If short-circuiting happens in the wire 58 or the voltage detecting section 11a, unnecessary voltage changes can be prevented in the storage battery Sa. This is because each female tab 50 has a resistor 57.

[0053] An excessively large current may flow through each female tab 50 due to short-circuiting in the wire 58 or the voltage detecting section 11a. In this case, the fuse of the female tab 50 melts, thereby preventing a fire or the like.

[0054] In the embodiment described above, each holding member 53 has been formed by bending a metal plate. Nonetheless, there is no limitation to the shape and the like of each holding member 53. The member 53 may have any shape, provided that it can reliably contact the connecting strip 33. For example, one of the holding members 53 may be formed by bending a metal plate, and the other holding member 53 may be an insulating member made of rubber or the like.

[0055] There are no limitation to the shape of the washer 30, either.

[0056] The apparatus described above is designed for use in an uninterruptible power supply system. Nevertheless, the apparatus can be used in any other system that has storage batteries.

[0057] The present invention is not limited to the embodiment described above. Various changes and modifications can be made within the scope and spirit of the invention.

Claims

1. An apparatus for managing a battery unit having a plurality of storage batteries, characterized by comprising:

a plurality of first voltage detecting means (11a, 11b, ... 11n) for detecting voltages of the storage batteries (Sa, Sb, ... Sn), respectively;
second voltage detecting means (13) for

detecting a total voltage of the battery unit (10);
defect detecting means (20) for detecting
defects in the storage batteries (Sa, Sb, ... Sn)
on the basis of the voltages detected by the
first voltage detecting means (11a, 11b, ... 11n);

abnormality detecting means (20) for detecting
an abnormal voltage in the battery unit (10) on
the basis of the voltage detected by the second
voltage detecting means;

temperature detecting means (12) for detecting
temperature in the battery unit (10);

battery life determining means (20) for deter-
mining a life of each of the storage batteries
(Sa, Sb, ... Sn) has dead, on the basis of the
temperature detected by the temperature
detecting means (12); and

information means (23) for informing results of
the detection performed by the defect detecting
means (20) and abnormality detecting means
(20) and results of the determination made by
the battery life determining means (20).

2. An apparatus according to claim 1, characterized in
that the storage batteries (Sa, Sb, ... Sn) are
sealed-type lead storage batteries and are con-
nected in series.
3. An apparatus according to claim 1, characterized
by further comprising operating mode determining
means (20) for determining an operation mode of
the battery unit (10).
4. An apparatus according to claim 3, characterized in
that the defect detecting means (20) detects
defects in the storage batteries (Sa, Sb, ... Sn) by
comparing the voltages detected by the first voltage
detecting means (11a, 11b, ... 11n) with a level set
on the basis of the operation mode determined by
the operating mode determining means (20).
5. An apparatus according to claim 3, characterized in
that the abnormality detecting means (20) detects
an abnormal voltage in the battery unit (10) by com-
paring the voltage detected by the second voltage-
detecting means (13) with a predetermined upper-
limit value and by comparing the voltage detected
by the second voltage-detecting means (13) with a
predetermined lower-limit value.
6. An apparatus according to claim 3, characterized in
that the operating mode determining means (20)
determines in which operation mode the battery
unit (10) is operating, float charge mode, discharge
mode, or recharge mode, on the basis of the volt-
age detected by the second voltage detecting
means (13); in said float charge mode, the voltage
of a power supply (2) connected to the battery unit

(10) is applied to a load (3) connected to the battery
unit (10), and the battery unit (10) is charged by vir-
tue of the voltage of the power supply (2); in said
discharge mode, the voltage of the battery unit (10)
is applied to the load (3) when the voltage of the
power supply (2) falls or is zero; and in said
recharge mode, the battery unit (10) is recharged
by virtue of the voltage of the power supply (2) after
the battery unit (10) has operated in the discharge
mode.

7. An apparatus according to claim 6, characterized in
that the defect detecting means (20) comprises first
defect detecting means, second defect detecting
means, and third defect detecting means; said first
detect detecting means detects defects in the stor-
age batteries (Sa, Sb, ... Sn) in accordance with
whether the voltages detected by the first voltage
detecting means (11a, 11b, ... 11n) are lower than a
predetermined low voltage V_2 , when the operation
mode determined by the operation mode determin-
ing means is the float charge mode; said second
detect detecting means detects defects in the stor-
age batteries (Sa, Sb, ... Sn) in accordance with
whether the voltages detected by the first voltage
detecting means (11a, 11b, ... 11n) are equal to or
higher than a predetermined high voltage V_3 , when
the operation mode determined by the operation
mode determining means is the float charge mode;
and the third defect detecting means for detecting
defects in the storage batteries (Sa, Sb, ... Sn) in
accordance with whether the voltages detected by
the first voltage detecting means (11a, 11b, ... 11n)
are lower than a predetermined low voltage V_1 ($< V_2$)
upon lapse of a prescribed time from the start of
the discharge mode, when the operation mode
determined (20) by the operation mode determining
means is the discharge mode.
8. An apparatus according to claim 6, characterized in
that the abnormality detecting means (20) com-
prises first abnormality detecting means and sec-
ond abnormality detecting means; said first
abnormality detecting means detects an abnormal
voltage in the battery unit (10) in accordance with
whether the voltage detected by the second voltage
detecting means (13) remains equal to or higher
than a predetermined maximum value for a pre-
scribed time; and the second abnormality detecting
means for detecting an abnormal voltage in the bat-
tery unit (10) in accordance with whether the volt-
age detected by the second voltage detecting
means (13) remains lower than a predetermined
minimum value for a prescribed time.
9. An apparatus according to claim 1, characterized in
that each of said storage batteries (Sa, Sb, ... Sn)
has a pair of electrodes (41):

10. An apparatus according to claim 9, characterized by further comprising connecting devices, each for the connecting one electrodes (41) of one storage battery to one first voltage detecting means.
- 5
11. An apparatus according to claim 10, characterized in that each of the connecting devices comprises a washer (30) to be removably attached to one electrode (41), a connecting member (50) to be removably connected to the washer (30), and a wire (58) 10 extending from the connecting member (50).
12. An apparatus according to claim 11, characterized in that the washer (30) has a ring-shaped part (32) and a connecting strip (33) extending outwardly 15 from the ring-shaped part (32) in a radial direction thereof; the connecting member (50) has a recess (52) for receiving and holding the connecting strip (33) of the washer (30) and a series circuit provided between the recess (52) and the wire (58) and composed of a fuse (56) and a resistor (57); and series 20 circuit connects the connecting strip (33) to the wire (58) when the connecting strip (33) is inserted into the recess (52).
- 25

30

35

40

45

50

55




FIG. 1





FIG. 2






FIG.4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10





FIG. 11



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 977 047 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
26.04.2000 Bulletin 2000/17

(51) Int. Cl.7: G01R 31/36

(43) Date of publication A2:
02.02.2000 Bulletin 2000/05

(21) Application number: 99114682.0

(22) Date of filing: 27.07.1999

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

- Motozu, Tamotsu,
c/o NTT Power and Building F. Inc
Tokyo (JP)
- Tsujikawa, Tomonobu,
c/o NTT Power and Building
Tokyo (JP)
- Kawagoe, Yuji,
c/o Nippon T. and T. East Corp.
Tokyo 163-8019 (JP)

(30) Priority: 28.07.1998 JP 21267198
31.07.1998 JP 21744198

(71) Applicant:
NTT Power and Building Facilities Inc.
Tokyo (JP)

(74) Representative:
Schmidt-Evers, Jürgen, Dipl.-Ing. et al
Patentanwälte Mitscherlich & Partner,
Sonnenstrasse 33
80331 München (DE)

(72) Inventors:
• Murao, Tetsuro,
c/o NTT Power and Building F. Inc.
Tokyo (JP)

(54) Apparatus for managing a battery unit having storage batteries

(57) The voltages V of storage batteries (S_a , S_b , ... S_n) are detected, and the voltage E of the battery unit (10) is detected. A defect in each storage battery is detected in accordance with the voltage V detected. An abnormal voltage of the battery unit (10) is detected in accordance with the voltage E detected. Further, the

temperature T of the battery unit (10) is detected, on the basis of which the expiration of each storage battery is determined. The defect detected, the abnormal voltage detected, and the expiration determined are informed.




FIG. 1

EP 0 977 047 A3



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 99 11 4682

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
X	WO 98 02933 A (DURACELL INC.) 22 January 1998 (1998-01-22)	1,3	G01R31/36
Y	* claim 1 *	2	
Y	----- PATENT ABSTRACTS OF JAPAN vol. 14, no. 576 (E-1016), 21 December 1990 (1990-12-21) & JP 02 250275 A (YUASA) * abstract *	2	
A	----- FR 2 742 601 A (RENAULT) 20 June 1997 (1997-06-20) * claim 1 *	1	
A	----- PATENT ABSTRACTS OF JAPAN vol. 1997, no. 9, 30 September 1997 (1997-09-30) & JP 09 129271 A (YAMAMOTO TOSHIO ET AL.) * abstract *	1	
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
			G01R
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 7 March 2000	Examiner Hoornaert, W
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

EPO FORM 1503 03.82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 11 4682

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

07-03-2000

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 9802933 A	22-01-1998	AU 3803097 A EP 0958632 A US 5955869 A	09-02-1998 24-11-1999 21-09-1999
JP 02250275 A	08-10-1990	JP 2077307 C JP 7120535 B	09-08-1996 20-12-1995
FR 2742601 A	20-06-1997	NONE	
JP 09129271 A	16-05-1997	NONE	

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

This Page Blank (uspto)

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☒ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.

This Page Blank (uspto)